

## QUICK REFERENCE GUIDE

### How to log into your voice mail

**Note: {HU} = Hang UP**

{from your own phone} press **[MW]** key

{from any other office phone} press: **[ICM] + 777** (listen to prompts)

{from auto-attendant} press: **[#] + your box number** (listen to prompts)

### ONCE LOGGED IN:

**{greeting}** press <4> or <greet> on display to manage personal greetings

**{see code}** press <67> for options, then <7> to enter a new 4-digit code (listen)

**{name}** press <76> to record your name. (listen to prompts)

**Note: if doing all 3 items, press <#> 3 times after before going to next item.**

When listening to messages, use display prompts for managing messages.

### HOW TO TRANSFER

**Note: do the following with the caller on the line**

**{outside callers to leave a message}** press: **[ICM] + [MW] + mailbox no. {HU}**

**{co-workers calling in to get messages}** press: **[ICM] + 777 {HU}**

**{callers to an extension}** press: **[ICM] + extension (announce call) {HU}**

-or- press **Hotkey** (if one is programmed) announce call - {HU}

**note: if co-worker wants caller to be sent to voice mail, simply select <MBOX> on display to instantly send caller to voice mail**

### HOT KEYS (for one touch calling/transfer & busy lamp)

All phones are pre-programmed with hot keys.

You can program /change hotkeys for whomever you would like.

- 1) press <#> <45> with receiver in cradle
- 2) select lit hot key you wish to program
- 3) type in extension + <HOLD>
- 4) select another or press <SPK> to end session

### CONFERENCE CALLING

**To add a second outside party to an existing outside call:**

press <FLASH> with caller on line

upon receiving a new dial tone, dial the parties phone number

once online with second party, press **[FLASH]** to add first party back in.

To add more parties in... press **[CONF]**

dial **extension** -or- dial **9** for another outside line then dial phone number  
when party is on with you, press **[CONF]** to join everyone together

## DS1000/2000 SYSTEM ADMINISTRATION GUIDE

To access system admin functions, you must first log into a mailbox with system admin privileges. If you wish to have this ability within your own personal mailbox, please arrange it with Teleworks which boxes should have such abilities.

### ONCE LOGGED IN:

Press **72** (SA system admin)

### System Admin Options Menu:

**I (4)** = Instruction Menu messages (*valid box numbers 000 - 007*)

*000 is the main greeting. You must record a greeting before using schedule override*

**A (2)** = Announcement messages (*valid box numbers 008 - 015*)

*These can be used for giving hours/directions/current events or specials etc...*

**S (7)** = Subscriber Maintenance, enter mailbox no when prompted.

**EA** = erase all messages

**EG** = erase greeting

**EN** = erase name (mailbox name)

**S** = Delete security code

**N** = Record a new name

**O (6)** = answer schedule override (*make sure you have recorded a greeting in the instruction msg*)

*Table number is usually number 1*

**C (2)** = Change override mailbox (*use 001- 007*)

**O (6)** = on or off

**(1)** = Message on hold

You can record a script or music through the handset and it will play whenever a caller is placed on hold.

Teleworks must predefine which source will play on hold whether it's the message on hold or an external audio source such as CD player.

**V (8)** = Voice Mail Version number (*current version is 130*)

### Changing Display name (also effects dial by name directory)

**Do not log into voice mail for this admin function. Do this from idle phone.**

1) Handset stays in cradle and select **PGM** on display options

2) press **MORE** until you see **NAME** show on display

3) select **NAME** and enter extension number + **[HOLD]**

4) enter name, same as you do on a cell phone (press **[Hold]** when completed)

5) enter another extension or press blinking **[SPK]** button to end session

### CHANGE SYSTEM TIME & DATE

press **#83**, enter 6 digit time in military format + **HOLD**, enter date + **HOLD... SPK**

## QUICK REFERENCE GUIDE

### How to log into your voice mail

**Note: {HU} = Hang UP**

From your own phone} press **[MW]** key

From any other office phone} press: **[ICM] + 777** (listen to prompts)

From auto-attendant} press: **[#] + your box number** (listen to prompts)

### ONCE LOGGED IN:

{greeting} press **<4>** or **<greet>** on display to manage personal greetings

{see code} press **<67>** for options, then **<7>** to enter a new 4-digit code (listen)

{name} press **<76>** to record your name. (listen to prompts)

**Note: if doing all 3 items, press <#> 3 times after before going to next item.**

When listening to messages, use display prompts for managing messages.

### HOW TO TRANSFER

**Note: do the following with the caller on the line**

{outside callers to leave a message} press: **[ICM] + [MW] + mailbox no. {HU}**

{co-workers calling in to get messages} press: **[ICM] + 777 {HU}**

{callers to an extension} press: **[ICM] + extension** (announce call) **{HU}**

-or- **press Hotkey** (if one is programmed) announce call - **{HU}**

note: if co-worker wants caller to be sent to voice mail, simply select **<MBOX>** on display to instantly send caller to voice mail

### HOT KEYS (for one touch calling/transfer & busy lamp)

All phones are pre-programmed with hot keys.

You can program /change hotkeys for whomever you would like.

press **[#] [4] [5]** with receiver in cradle select lit hot key

you wish to program

type in extension + **[HOLD]**

select another or press **[SPK]** to end session

### To program personal speed dial (on top 10 keys)

#### receiver in cradle

on the display select **<PGM> + <SPD>**

select 1 of top 10 keys to program + **[HOLD]**

press **[9] [0] + [HOLD]**

enter complete phone number + **[HOLD]** press **[HOLD]** again and enter a

name + **[HOLD]** to complete **[SPK]** to end session